

EE 567

Homework 2

Due Monday, September 11, 2017

Work all 6 problems.

Problem 1. Lathi and Ding 2.1-2.

Problem 2. Lathi and Ding 2.1-3.

Problem 3. Lathi and Ding 2.1-6.

Problem 4. Lathi and Ding 2.1-8 (a), (b), (c).

Problem 5. Pulse Coded Modulation (PCM) is to be used to encode a signal. The signal ranges between the values -2 and $+2$. There are 4 bits or 16 levels (hence 16 code numbers) available. The levels assigned have symmetry like we demonstrated in class. The first three sample values obtained (before quantization) are 0.9 , 2.0 , and -1.4 , respectively.

- a. Find the quantized values for the three sample values.
- b. Find the corresponding PCM sequences for the quantized values.

Problem 6. Let $s(t) = 10 \cos(2\pi ft + \pi/4)$ where $f = 20$ Hz. Let us sample $s(t)$ at the sampling rate of $f_s = 80$ Hz to obtain the discrete time signal $s(nT_s) = 10 \cos(2\pi fnT_s + \pi/4)$ where $T_s = 1/f_s$, for $n = 0, 1, 2, \dots, 40$. Using the PCM example in class as a guide compute the quantized PAM signal and the corresponding PCM codeword assuming you have 8 bits or 256 levels to represent the quantized signal.

Note: In this problem you are to use Matlab.