

EE 567

Homework 10

Due Tuesday, November 12, 2019

Work all 2 problems.

Problem 1. A binary communication system is used where at the receiver the test statistic is $z(T) = ca_i + n_0$, $i = 1, 2$ where $a_1 = +1$ and $a_2 = -1$ and $c = 1$ if a signal is present and $c = 0$ if a signal is not present. The noise n_0 is distributed as

$$p(n_0) = \begin{cases} n_0 + 1.0, & -1.0 \leq n_0 \leq 0 \\ -(n_0 - 1.0), & 0 \leq n_0 \leq 1.0 \\ 0 & \text{elsewhere.} \end{cases}$$

However, the receiver is just interested in detecting whether or not the signal is actually present. If the signal is not present the noise n_0 is still present and if the signal is present the noise is present also. So, the receiver designer decides to take the absolute value of the test statistic and compare this to a threshold. If $|Z(T)| > T_0$, for some T_0 , then a signal is declared present, otherwise, it is not.

- Find T_0 such that the probability of false alarm is 10^{-4} .
- If a signal is present find the probability that you would detect it with this logic.

Problem 2. Suppose we receive a BPSK signal of the form

$$r(t) = A_1 \cos(2\pi f_c t) + n(t), \quad 0 \leq t \leq T$$

where $n(t)$ is a noise process, $T = 1$ sec, $f_c = 1$ kHz and $A_1 = \pm 2$ with equal probability. The signal is demodulated in an optimal manner and then an optimal threshold is used in making a decision. For demodulation assume the received signal $r(t)$ is mixed with a cosine wave of amplitude 1 with the same frequency and phase of the transmitted signal of interest and then low pass filtered by integrating from 0 to T . With this approach suppose at the

output of the demodulator (just prior to the threshold comparator) the noise (call it n) is characterized by the Laplacian density

$$p(n) = \frac{1}{\sqrt{2}\sigma} e^{-|n|\sqrt{2}/\sigma}, \quad (-\infty < n < \infty)$$

where we will take $\sigma = 1$.

- a. Using the optimal detector (with the corresponding optimal threshold) as described above compute the probability of a correct decision, P_c , for the value of A_1 . You may assume that f_c is known to the receiver.
- b. Now suppose an interfering signal is also present so that

$$r(t) = A_1 \cos(2\pi f_c t) + A_2 \cos(2\pi f_c t + \pi/4) + n(t) \quad 0 \leq t \leq T.$$

However, the receiver does not know the interfering signal is present so the receiver does not change the threshold used in part (a) nor does the receiver make any other modifications. Find the value of A_2 so that if a symbol is transmitted with $A_1 = 2$ then the probability of a correct decision for that symbol is now 0.1.

- c. Using the value of A_2 found in part (b) find the probability of a correct decision at the receiver assuming $A_1 = -2$.
- d. Combine parts (b) and (c) to compute the overall probability of a correct decision in the presence of the interferer.
- e. Again using the value of A_2 found in part (b) find the overall probability of a correct decision if the interferer's frequency is changed such that now $f_0 = 0.8$ kHz and thus

$$r(t) = A_1 \cos(2\pi f_c t) + A_2 \cos(2\pi f_0 t + \pi/4) + n(t) \quad 0 \leq t \leq T.$$