

## 15.0 Wide Sense Stationary (WSS) Random Processes

### 15.1 Definitions

**Definition:** A random process  $X(u, t)$  is stationary if

$$F(\mathcal{T}_\tau(\underline{x})) = F(\underline{x})$$

**Definition:** A random process is wide sense stationary if it has time invariant  $1^{st}$  and  $2^{nd}$  order statistics.

So, 1)  $\mu_X(t) = \mu_X(t + \tau)$  Let  $\tau = -t$

$$\mu_X(t) = \mu_X(0) \longrightarrow \text{some constant}$$

2)  $R_X(t_1, t_2) = R_X(t_1 + \tau, t_2 + \tau)$  Let  $\tau = -t_2$

$$R_X(t_1, t_2) = R_X(t_1 - t_2, 0) = R_X(t_1 - t_2)$$

### 15.2 Power Spectral Density (PSD) in Discrete Time Systems

Positive Semi-Definite Property

$$\sum_{k=-N}^N \sum_{\ell=-N}^N a_k R_X(k, \ell) a_\ell^* \geq 0 \quad \forall N \in \mathcal{T} \quad (\text{discrete})$$

Let  $a_k = e^{-i2\pi f k}$ . Assume  $X(u, n)$  is WSS.

$$\sum_{k=-N}^N \sum_{\ell=-N}^N e^{-i2\pi f(k-\ell)} R_X(k-\ell) \geq 0$$

Let  $m = k - \ell$ ;  $n = k + \ell$

$$\implies \sum_{m=-2N}^{2N} (2N + 1 - |m|) e^{-i2\pi f m} R_X(m) \geq 0 \quad (\text{think})$$

divide by  $(2N + 1)$ , take limit,

$$\lim_{N \rightarrow \infty} \sum_{m=-2N}^{2N} \left(1 - \frac{|m|}{2N + 1}\right) e^{-i2\pi f m} R_X(m) \geq 0$$

Define

$$S_X(f) = \underbrace{\sum_{m=-\infty}^{\infty} R_X(m)e^{-i2\pi fm}}_{\text{Power Spectral Density}}, \quad f \in \left[-\frac{1}{2}, \frac{1}{2}\right]$$

So, PSD = Fourier Transform of autocorrelation function.

### Properties

1)  $R_X(m)$  are Fourier Series coefficient for  $S_X(f)$ .

$$R_X(m) = \int_{-\frac{1}{2}}^{\frac{1}{2}} S_X(f)e^{i2\pi fm}df$$

$$R_X(0) = \int_{-\frac{1}{2}}^{\frac{1}{2}} S_X(f)df$$

$$R_X(0) = E[|X(u)|^2]$$

2) Periodic:  $S_X(f) = S_X(f + k)$  for integer  $k$ .

3) Any P.S.D. correlation has a non-negative PSD.

4)  $S_X(f)$  is real.

5) If  $R_X(u)$  is real, then  $S_X(f) = S_X(-f)$ .